

Features

- Formerly Fullec brand
- Extremely low capacitance
- Very high bandwidth
- Small package, minimal PCB area
- RoHS compliant*

Applications

- GR-1089
- ITU K.20 and K.21
- ADSL2+ and VDSL2 linecards
- LAN, WAN equipment

FVC Series Voltage Control Devices

Voltage Control

Bourns[®] voltage control devices are used with high-speed series protectors to protect sensitive circuits from electrical disturbances caused by lightning-induced surges, inductive-coupled spikes, and AC power cross conditions. The unique structure and characteristics of the device are used to create an overvoltage protection device with precise and repeatable turn-on characteristics with low voltage overshoot and high surge current capabilities.

Specifications

	Surge Rating Electrical Characteristics								
Part Number	lpp (A)	V _{DRM} (V)	V _S (V)	V _T (V)	I _{DRM} (μΑ)	I _S (mA)	I _Т (А)	I _H (mA)	C _O (pF)
FVC2300	4	190	260	3	5	400	1	150	6
FVC3100	4	275	350	3	5	400	1	150	6

Ipp (peak pulse current) - maximum rated peak impulse current with 1.2/50 μs waveform

 $V_{\mbox{DRM}}$ (peak off-state voltage) - maximum voltage that can be applied while maintaining off state measured at $I_{\mbox{DRM}}$

 V_S (switching voltage) - maximum voltage prior to switching to on-state measured at 100 V/ $\!\mu s$

 $V_{\ensuremath{\text{T}}}$ (on-state voltage) - maximum voltage measured at rated on-state current

 $I_{\ensuremath{\mathsf{DRM}}}$ (leakage current) - maximum peak off-state current measured at $V_{\ensuremath{\mathsf{DRM}}}$

 I_S (switching current) - maximum current required to switch to on state I_T (on-state current) - maximum rated continuous on-state current

IH (holding current) - minimum current required to maintain on state

 $C_{\mbox{O}}$ (off-state capacitance) - typical off-state capacitance measured at 1 MHz with a 2 V bias

Typical Performance Characteristics



General Notes:

- All measurements are at an ambient temperature of 25 °C. Ipp applies to -40 °C through +85 °C.
- IPP is a repetitive surge rating and is designed to be maintained for the life of the product.
- The devices are bidirectional. All electrical parameters and surge ratings apply to forward and reverse polarities.
- Special voltage (VS and VDRM) and holding current (IH) requirements are available upon request.

*RoHS Directive 2002/95/EC Jan 27 2003 including Annex. Specifications are subject to change without notice. Customers should verify actual device performance in their specific applications

FVC Series Voltage Control Devices

BOURNS

Product Dimensions



Dim.	Minimum	Maximum		
А	<u>2.29</u> (0.090)	<u>3.00</u> (0.118)		
В	<u>4.50</u> (0.177)	<u>5.40</u> (0.213)		
С	<u>1.25</u> (0.050)	<u>1.65</u> (0.065)		
D	<u>3.90</u> (0.154)	<u>4.65</u> (0.183)		
E	<u>0.76</u> (0.030)	<u>1.52</u> (0.060)		
F	<u>0.15</u> (0.006)	<u>0.30</u> (0.012)		
G	_	<u>0.20</u> (0.008)		
Н	<u>1.95</u> (0.077)	<u>2.24</u> (0.088)		

MM DIMENSIONS: (INCHES)

How to Order



Typical Part Marking



*TRANSITION FROM FULTEC TRADEMARK TO BOURNS TRADEMARK IN 2009.

FVC Series Voltage Control Devices

BOURNS

Packaging Specifications









Symbol	Dim.			
A0	$\frac{2.72 \pm 0.10}{(0.109 \pm 0.004)}$			
В0	$\frac{5.25 \pm 0.10}{(0.210 \pm 0.004)}$			
d	$\frac{1.55 \pm 0.05}{(0.061 \pm 0.002)}$			
D	<u>330.0</u> (13.0)			
D1	50.0 (1.969) MIN.			
D2	$\frac{13.50 \pm 1.0}{(0.531 \pm 0.039)}$			
E	$\frac{1.75 \pm 0.10}{(0.069 \pm 0.004)}$			
F	$\frac{5.50 \pm 0.05}{(0.217 \pm 0.002)}$			
К0	2.66 (0.105) MAX.			
Р	$\frac{4.00 \pm 0.10}{(0.157 \pm 0.004)}$			
P0	$\frac{4.00 \pm 0.10}{(0.157 \pm 0.004)}$			
P1	$\frac{2.00 \pm 0.05}{(0.079 \pm 0.002)}$			
t	0.60 (0.024) MAX.			
W	$\frac{12.00 \pm 0.30}{(0.472 \pm 0.012)}$			
W1	18.4 (0.724) MAX.			

DIMENSIONS: MM (INCHES)



Asia-Pacific: Tel: +886-2 2562-4117 • Fax: +886-2 2562-4116 Europe: Tel: +41-41 768 5555 • Fax: +41-41 768 5510 The Americas: Tel: +1-951 781-5500 • Fax: +1-951 781-5700 www.bourns.com

01/09

COPYRIGHT©2009, BOURNS, INC. LITHO IN U.S.A. e 01/09 FU0903 Specifications are subject to change without notice. Customers should verify actual device performance in their specific applications