



# PB-03 Specification

Version V1.0.0

Copyright©2021



## Content

1. Product Overview.....	4
1.1. Characteristic.....	5
2. Main parameters.....	5
2.1. Static electricity requirements.....	6
2.2. Electrical characteristics.....	6
2.3. BLE RF performance.....	6
2.4. Power consumption.....	7
3. Appearance dimensions.....	8
4. Pin definition.....	9
5. Schematic.....	11
6. Antenna parameters.....	12
6.1. Test conditions for the antenna.....	12
6.2. Antenna S parameter.....	13
6.3. Antenna Gain and Efficiency.....	13
6.4. Antenna field type diagram.....	14
7. Design guidance.....	15
7.1. Module application circuit.....	15
7.2. Antenna layout requirements.....	16
7.3. Power supply.....	16
7.4. GPIO.....	18
8. Flow welding curve diagram.....	19
9. Product related models.....	20
10. Product packaging information.....	21
11. Contact us.....	21
Disclaimer and copyright notice.....	22
Notice.....	22

# 1. Product Overview

PB-03 is a BLE module developed by Shenzhen Ai-Thinker Technology Co.,Ltd.The core processor chip PHY6252(SSOP24)of this module is a BLE SoC with high integration and low power consumption,which is specially designed for various applications such as IoT,mobile devices,wearable electronic devices and smart homes.

PHY6252(SSOP24)chip has industry-leading low power consumption performance and RF performance,it supports BLE 5.2.The chip built in 64 KB SRAM,256KB flash,96 KB ROM,256bit efuse.The chip supports a variety of low-power working states and can meet the power consumption requirements of various application scenarios.RF output power can be adjusted to achieve the best balance among communication distance,communication rate and power consumption.

PB-03 module provide rich peripheral interfaces,including UART,PWM,ADC,I2C,SPI,PDM,DMA and up to 19 IOs.

PB-03 module has many unique hardware security mechanisms.Hardware encryption accelerator supports AES algorithm.

PB-03 module supports BLE with low power consumption:BLE 5.2 and BLE mesh.Bluetooth rate support:125Kbps,500Kbps,1Mbps,2Mbps.Support broadcast expansion,multi-broadcast,channel selection.




Figure 1 Main chip architecture diagram

## 1.1. Characteristic

- Support BLE5.2,rate support:125Kbps,500Kbps,1Mbps,2Mbps
- Own 64 KB SRAM, 256KB flash,96 KB ROM, 256bit efuse
- Support UART/GPIO/ADC/PWM/I2C/SPI/PDM/DMA interface
- Adopt SMD-52 package
- Support multiple sleep modes,deep sleep current is less than 1uA
- Support for serial local upgrade and remote Firmware upgrade(FOTA)
- Universal AT instructions can be used easy and quickly
- Support for secondary development,with an integrated Windows development environment

## 2. Main parameters

**Table 1 Description of the main parameters**

<b>Model</b>	PB-03
<b>Package</b>	SMD-52
<b>Size</b>	16.6*13.2*2.8(±0.2)mm
<b>Antenna</b>	On-board antenna
<b>Frequency</b>	2400~2483.5MHz
<b>Operating temperature</b>	-40°C~85°C
<b>Storage temperature</b>	-40°C~125°C,<90%RH
<b>Power supply</b>	Voltage 2.7V~3.6V,Current>200mA
<b>Interface</b>	UART/GPIO/ADC/PWM/I2C/I2S/SPI/PDM/DMA
<b>IO</b>	19
<b>UART rate</b>	Default 115200 bps
<b>Bluetooth</b>	BLE 5.2
<b>Security</b>	AES-128
<b>SPI Flash</b>	256KB

## 2.1. Static electricity requirements

PB-03 is an electrostatic sensitive device, and special precautions must be taken when handling it.



Figure 2 ESD anti-static diagram

## 2.2. Electrical characteristics

Table 2 Electrical characteristics table

Parameters		Conditions	Min.	Typical value	Max.	Unit
Power supply voltage		VDD	2.7	3.3	3.6	V
I/O	$V_{IL}/V_{IH}$	-	-0.3/0.75V DD	-	0.25VDD/VDD +0.3	V
	$V_{OL}/V_{OH}$	-	N/0.8VIO	-	0.1VIO/N	V
	$I_{MAX}$	-	-	-	12	mA

## 2.3. BLE RF performance

Table 3 BLE RF performance table

Description	Typical values			Unit
Operating frequency	2400-2483.5			MHz
<b>Output power</b>				
Mode	Min.	typical value	Max.	Unit
BLE 2Mbps	-20	8	10	dBm
BLE 1Mbps	-20	8	10	dBm
BLE 500Kbps	-20	8	10	dBm
BLE 125kbps	-20	8	10	dBm
<b>Receiving sensitivity</b>				
Mode	Min.	typical value	Max.	Unit

BLE 2Mbps	-	-93	-	dBm
BLE 1Mbps	-	-96	-	dBm
BLE 500Kbps	-	-97	-	dBm
BLE 125Kbps	-	-102	-	dBm

## 2.4. Power consumption

The following power consumption data are based on a 3.3V power supply, ambient temperature of 25°C and measured using an internal regulator.

- All measurements were completed without the SAW filter at the antenna interface.
- All emission data were measured based on the TX\_Burst\_Test&RX\_Burst\_Test mode

**Table 4 Power consumption table**

Mode	Min.	Average value	Max.	Unit
TX_Burst_Test Power output 8dBm	-	11.5	-	mA
TX_Burst_Test Power output 5dBm	-	9	-	mA
TX_Burst_Test Power output 0dBm	-	8	-	mA
RX_Burst_Test	-	9.4	-	mA
Deep Sleep(With broadcast,1 second interval)	-	50.58	-	uA
Deep Sleep(With broadcast,2 seconds interval)	-	28.25	-	uA
Deep Sleep(Without broadcast)	-	7.2	-	uA
Power Off	-	0.57	-	uA

### 3. Appearance dimensions




Figure 3 Appearance diagram pictures is for reference only,subject to physical objects)




Figure 4 Module size diagram



**Table 6 Pin function definition table**

No.	Name	Function
1,2,11,14, 36-48,50-53	GND	Ground(Power negative electrode)
3	3V3	Power supply positive electrode
4,7,9,10,15,17,20,2 1,25,34,35	NC	Empty
5	P24	GPIO24/ADC input 2
6	P7	GPIO7
8	P31	GPIO31
12	P16	GPIO16/32.768KHz crystal input
13	P17	GPIO17/32.768KHz crystal output
16	P32	GPIO32
18	P11	GPIO11/ADC input 0
19	P18	GPIO18/ADC input 7/PGA negative input
22	P2	GPIO2/SWD debug data inout
23	P3	GPIO3/SWD debug clock
24	P14	GPIO14/ADC input 3
26	P0	GPIO0
27	P34	GPIO34
28	P33	GPIO33
29	P23	GPIO23/ADC input 1/micbias reference
30	P10	RXD/GPIO10
31	P9	TXD/GPIO9
32	P20	GPIO20/ADC input 9/PGA positive input
33	P15	GPIO15/ADC input 4/micbias output

## 5. Schematic




Figure 6 Module schematic

## 6. Antenna parameters

### 6.1. Test conditions for the antenna



**Figure 7 Antenna test conditions**

## 6.2. Antenna S parameter





Figure 8 Antenna S parameters

## 6.3. Antenna Gain and Efficiency

Table 7 Antenna Gain and efficiency

Frequency ID	1	2	3	4	5	6	7	8	9	10	11
Frequency(MHz)	2400.0	2410.0	2420.0	2430.0	2440.0	2450.0	2460.0	2470.0	2480.0	2490.0	2500.0
Gain(dBi)	1.89	1.98	1.86	1.95	1.98	2.04	2.06	1.98	1.83	1.75	1.63
Efficiency(%)	60.23	61.27	59.41	60.36	59.85	59.53	59.10	57.85	56.20	55.85	54.62

### 6.4. Antenna field type diagram




**Figure 9 Antenna field type diagram**

## 7. Design guidance

### 7.1. Module application circuit

( $\geq 200\text{mA}$ , suggest use DC-DC or LDO independent power supply)



**Figure 10 Application circuit diagram**

Note:

- Because the PB-03M does not have the reset pin, we can achieve the reduction by power off, we can restore the module with a PMOS to achieve the reduction of power off.
- TX&RX serial port line, 2 resistors are reserved, in series in the line. The 3.3V voltage used to prevent the serial port affects the reset of the module.

## 7.2. Antenna layout requirements

- The installation position on the motherboard suggests the following 2 ways:

Scheme 1: Put the module on the edge of the motherboard, and the antenna area out of the motherboard edge

Scheme 2: Put the module on the edge of the motherboard, and empty an area along the antenna position.

- To meet the performance of the on-board antenna, metal parts are not placed around the antenna, away from the high-frequency device





Figure 11 Schematic diagram of the antenna layout

## 7.3. Power supply

- Recommended 3.3V voltage, peak current over 200mA.
- Power supply is recommend to use LDO; If the DC-DC is used, the ripple is recommended to be controlled within 30mV
- The DC-DC power supply circuit proposes to reserve the dynamic response capacitance to optimize the output ripple with large load changes.
- 3.3V power interface it is recommended to add ESD devices.



**Figure 12 The DC-D C antihypertensive circuit diagram**

## 7.4. GPIO

- Some IO ports are lead outside the module,if using,a proposed resistance of 10-100 ohms on the IO port.This suppresses the overshoot and enables smoother levels on both sides,helping for both EMI and ESD.
- The up and down of the special IO port should refer to the use instructions of the specification,which will affect the start-up configuration of the module.
- The IO port of the module is 3.3V,if the main control does not match the IO port level of the module,the level conversion circuit should be increased.
- If the IO port is directly connected to the peripheral interface,or terminals such as pin header,it is recommended to reserve ESD devices at the IO port line near the terminal.




Figure 13 Level convert circuit

## 8. Flow welding curve diagram




Figure 14 Flow welding diagram

## 9. Product related models

**Table 8 Product related model list**

Model	Power Supply	Package	Size	Antenna
PB-03F	2.7V~3.6V, I>200mA	SMD-22	24.0*16.0*3.1(±0.2)mm	On-board PCB
PB-03M	2.7V~3.6V, I>200mA	DIP-18 Gold finger plugin	18.0*18.0*2.8(±0.2)mm	On-board PCB
PB-03	2.7V~3.6V, I>200mA	SMD-61	16.6*13.2*2.8(±0.2)mm	On-board PCB
NodeMCU- PB-03F-Kit	5V, I>200mA	DIP-30	49.3*25.4*12.9(±0.2)mm	On-board PCB
NodeMCU- PB-03M-Kit	5V, I>200mA	DIP-20	32.8*28.6*18.3(±0.2)mm	On-board PCB
NodeMCU- PB-03-Kit	5V, I>200mA	DIP-30	49.3*25.4*12.9(±0.2)mm	On-board PCB
Product related information: <a href="https://docs.ai-thinker.com">https://docs.ai-thinker.com</a>				

## 10. Product packaging information

PB-03 module was packaged in a tape, 900pcs/reel. As shown in the below image:



Figure 15 Package and packing diagram

## 11. Contact us

[Ai-Thinker official website](#)

[Office forum](#)

[Develop DOCS](#)

[LinkedIn](#)

[Tmall shop](#)

[Taobao shop](#)

[Alibaba shop](#)

[Technic support email: support@aithinker.com](mailto:support@aithinker.com)

[Domestic business cooperation: sales@aithinker.com](mailto:sales@aithinker.com)

[Overseas business cooperation: overseas@aithinker.com](mailto:overseas@aithinker.com)

Company Address: Room 403,408-410, Block C, Huafeng Smart Innovation Port, Gushu 2nd Road, Xixiang, Baoan District, Shenzhen.

Tel: +86-0755-29162996



Wechat mini program



Wechat official account

## Disclaimer and copyright notice

The information in this article,including the URL address for reference,is subject to change without notice.

The document is provided "as is" without any guarantee responsibility,including any guarantee for merchantability,suitability for a specific purpose,or non-infringement,and any guarantee mentioned elsewhere in any proposal,specification or sample.This document does not bear any responsibility,including the responsibility for infringement of any patent rights arising from the use of the information in this document.This document does not grant any license for the use of intellectual property rights in estoppel or other ways,whether express or implied.

The test data obtained in the article are all obtained from Ai-Thinker's laboratory tests,and the actual results may vary slightly.

All brand names,trademarks and registered trademarks mentioned in this article are the property of their respective owners,and it is hereby declared.

The final interpretation right belongs to Shenzhen Ai-Thinker Technology Co.,Ltd.

## Notice

Due to product version upgrades or other reasons,the contents of this manual may be changed.

Shenzhen Ai-Thinker Technology Co.,Ltd.reserves the right to modify the contents of this manual without any notice or prompt.

This manual is only used as a guide.Shenzhen Ai-Thinker Technology Co.,Ltd.makes every effort to provide accurate information in this manual.However,Shenzhen Ai-Thinker Technology Co.,Ltd.does not guarantee that the contents of the manual are completely free of errors.All statements and information in this manual And the suggestion does not constitute any express or implied guarantee.