

rfmd.com

SGL-0263(Z)

1400 MHz to 2500 MHz SILICON GERMANIUM CASCADABLE LOW NOISE AMPLIFIER



RFMD Green, RoHS Compliant, Pb-Free (Z Part Number) Package: SOT-363

Product Description

The SGL-0263 is a high performance SiGe HBT MMIC low noise amplifier featuring 1 micron emitters with F_T up to 50 GHz. This device has an internal temperature compensation circuit permitting operation directly from supply voltages as low as 2.5V. The SGL-0263 has been characterized at V_D =3V for low power and 4V for medium power applications. Only two DC-blocking capacitors, 2 input matching components, a bias resistor, and an optional RF choke are required for operation from 1400 MHz to 2500 MHz.



Features

- High Input/Output Intercept
- Low Noise Figure: 1.3dB typ. at 1900 MHz
- Low Power Consumption
- Single Voltage Supply Operation
- Internal Temperature Compensation

Applications

- Receivers, GPS, RFID
- Cellular, Fixed Wireless, Land Mobile

| Parameter | Specification (V _S =3V) | | | Specification (V _S =4V) | | | Unit | Condition |
|--|------------------------------------|------|------|------------------------------------|------|------|------|------------------------------|
| Farameter | Min. | Тур. | Max. | Min. | Тур. | Max. | Unit | Condition |
| Small Signal Gain | 12.1 | 13.4 | 14.7 | | 13.8 | | dB | 1900MHz |
| | | 12.5 | | | 12.9 | | dB | 2100MHz |
| | | 10.8 | | | 11.3 | | dB | 2400MHz |
| Output Power at 1dB Compres- sion | 3.5 | 5.5 | | | 11.4 | | dBm | 1900MHz |
| | | 6.8 | | | 12.3 | | dBm | 2100MHz |
| | | 7.9 | | | 12.8 | | dBm | 2400MHz |
| Input Third Order Intercept Point Tone Spacing=1MHz, P _{OUT} per tone=-13dBm | 7.5 | 9.5 | | | 15.1 | | dBm | 1900MHz |
| | | 13.5 | | | 16.8 | | dBm | 2100MHz |
| | | 15.5 | | | 18.4 | | dBm | 2400MHz |
| Noise Figure | | 1.3 | 1.7 | | 1.9 | | dB | 1900MHz, Z _S =50Ω |
| | | 1.5 | | | 2.1 | | dB | 2100MHz, Z _S =50Ω |
| | | 2.0 | | | 2.8 | | dB | 2400MHz, Z _S =50Ω |
| Input Return Loss | 10.0 | 13.3 | | | 21.9 | | dB | 1900 MHz |
| Output Return Loss | 10.0 | 12.9 | | | 17.4 | | dB | 1900MHz |
| Reverse Isolation | | 20.7 | | | 21.0 | | dB | 1900 MHz |
| Device Current | 9.0 | 12.5 | 15.0 | | 23.0 | | mA | |
| Thermal Resistance (Junction to Lead) | | 255 | | | | | °C/W | |

Test Conditions: 1400MHz to 2500MHz Application Circuit, T_{LEAD}=25 °C, Z_0=Z_L=50\Omega

RF MICRO DEVICES®, RFMD®, Optimum Technology Matching®, Enabling Wireless Connectivity^M, PowerStar®, POLARIS^M TOTAL RADIO^M and UttimateBlue^M are trademarks of RFMD, LLC. BLUETOOTH is a trademark owned by Bluetooth SIG, Inc., U.S.A. and licensed for use by RFMD. All other trade names, trademarks and registered trademarks are the property of their respective owners. ©2006, RF Micro Devices. Inc.

SGL-0263(Z)



Absolute Maximum Ratings

| | , | |
|--|------------|-------|
| Parameter | Rating | Unit |
| Max Device Current (I _D) | 45 | mA |
| Max Device Voltage (V _D) | 5 | V |
| Max RF Input Power | +10 | dBm |
| Max Junction Temp (T _J) | +150 | °C |
| Operating Temp Range (T _L) | -40 to +85 | °C |
| Max Storage Temp | +150 | °C |
| ESD | 1A | Class |
| MSL | 1 | |

Operation of this device beyond any one of these limits may cause permanent damage. For reliable continuous operation, the device voltage and current must not exceed the maximum operating values specified in the table on page one. Bias Conditions should also satisfy the following expression:

 $I_D V_D < (T_J - T_L) / R_{TH}$, j-l



Caution! ESD sensitive device.

Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical perfor-mance or functional operation of the device under Absolute Maximum Rating condi-tions is not implied.

RoHS status based on EUDirective2002/95/EC (at time of this document revision).

The information in this publication is believed to be accurate and reliable. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.



Typical RF Performance Over Lead Temperature at 3 V and 4 V -- 1400-2500 MHz Evaluation Board



SGL-0263(Z)



SGL-0263(Z)

| Pin | Function | Description | |
|------|-------------|--|--|
| 1 | N/C | No electrical connection. Provide an isolated (ungrounded) solder pad for mounting integrity. | |
| 3 | RF IN | RF input pin. This pin requires the use of an external DC-blocking capacitor chosen for the frequency of operation. | |
| 4 | DC BIAS | Voltage supply connection. Bypass with suitable capacitors. | |
| 2, 5 | GND | Connection to ground. Provide via holes as close to ground leads as possible to reduce ground inductance and schieve optimum RF performance. | |
| 6 | RF OUT/BIAS | RF output and voltage supply. DC voltage is present on this pin, therefore a DC-blocking capacitor is necessary for proper operation. | |



Suggested Pad Layout

Notes:

1. Provide a ground pad area under device pins 2 & 5 with plated via holes to the PCB ground plane.

RFMD

rfmd.com

2. We recommend 1 or 2 ounce copper. Measurements for this data sheet were made on a 31 mil thick Getek with 1 ounce copper on both sides.

Package Drawing

Dimensions in inches (millimeters) Refer to drawing posted at www.rfmd.com for tolerances.







1400 MHz to 2500 MHz Application Circuit



 $R_{\rm pc}$ may be introduced as a voltage dropping resistor for use with supply voltages greater than the desired device bias voltage.

Evaluation Board Layout







Alternate Marking with Trace Code Only



Ordering Information

| Part Number | Description | Reel Size | Devices/Reel | |
|----------------|--|-----------|--------------|--|
| SGL-0263 | Tn-Lead | 7" | 3000 | |
| SGL-0263Z | RoHS Compliant | 7" | 3000 | |
| SGL-0263Z-EVB1 | SGL-0263Z-EVB1 1400-2500 MHz Application Circuit | | N/A | |