

KFF6050A 1030 MHz TCAS BPF

Rev 1 - Origin Date: July 11, 2005 - Revision Date: August 24, 2005

Features

- High Rejection
- Low Loss
- Symmetrical Attenuation

Description

Rugged mount, silver (Ag) coated ceramic filter. Developed for use in TCAS applications.

Weight: 20.4 grams typical

Material: Filter is composed of a ceramic block plated with Ag and a bracket made of 60-40 tin lead plated cold roll steel.



Electrical Specifications

Parameter	Frequency (MHz)	Typical @ 25ºC	Spec. @ 25⁰C
Passband Insertion Loss	1025-1035	2.0 dB	2.5 dB max
Passband Return Loss	1025-1035	15.0 dB	10.0 dB min
Attenuation	1000	25.0 dB	18.0 dB min
	1100	45.0 dB	35.0 dB min

Note: Supplier shall test each filter to the critical electrical specifications of the above table. Any subsequent audits may deviate from in value due to measurement repeatability among different test systems. Such deviations shall not exceed the following limits:

Specification Allowance			
Insertion Loss	0.1 dB		
Return Loss	1.0 dB		
Stopbands	1.0 dB		

• This product is covered by one or more of the following U.S. and foreign patents including: US 4,692,726;US 4,742,562; US 4,800,348;US 4,829,274;US 5,146,193;EP 0573597;DE 0573597;JP 508149/92;KR 142171;US 5,126,700;US 5,278,329;US 5,250,916;US 5,327,109;US 5,488,335;CA 2114029;FR 9306297;GB 2273393;JP 3205337;KR 115113;CN 93106228;4;US 5,512,866;EP 0706719;DE 0706719;DE 0706719;GB 0706719;CB 0706719;CN 95190359;4;US 5,602,518;US 5,721,520;US 5,745,018;EP 0910875;DK 0910875;FR 0910875;GE 0910875;JE 0910875;JE

•CTS Corporation 2006 reserves all copyrights in the layout, design and configuration of the patterns on this product."

Document No. 008-0256-0

Page 1 of 2



KFF6050A 1030 MHz TCAS BPF

Mechanical Drawing

Rev 1 – Origin Date: July 11, 2005 – Revision Date: August 24, 2005



٠

Electrical response



Frequency, MHz

PCB Layout



MOUNTING VARIES BY INDIVIDUAL CUSTOMER.

Packaging and Marking



This product is shipped in pre-formed foam trays.



7 15 Slot Foam Trays

(100 max per box)

Document No. 008-0256-0

Page 2 of 2

Rev. X4VH

- CTS Electronic Components - www.ctscorp.com - 171 Covington Drive - Bloomingdale, IL 60108 -