

# Directional 30 dB SMA Coupler From 2 GHz to 18 GHz Rated to 50 Watts



## Couplers Technical Data Sheet

PE2CP000-30

#### **Features**

- Directional Coupler
- 2 to 18 GHz Frequency Range
- Coupling 30±1 dB

- Directivity > 10 dB
- VSWR < 1.5:1</li>
- Max Power 50 Watts (CW)

### **Applications**

- Test and Measurement
- Military Communications
- Commercial Communications
- · Wireless Communications
- SATCOM

#### **Description**

Directional couplers are indispensable components for isolating, separating and combining signals. For example, they provide a simple way of sampling microwave signals. They also can make accurate attenuator measurements since reflections are eliminated. The PE2CP000-30 is a 30 dB directional coupler that operates from 2 to 18 GHz with 10 dB directivity minimum and 1.5:1 VSWR maximum. The package interface uses SMA female connectors, and is also RoHS compliant.

The PE2CP000-30 is part of Pasternack's family of directional/dual-directional couplers that offer coupling ratio up to 50 dB with excellent performance featuring high directivity, low insertion loss and VSWR. They are available in both narrow and broad bandwidths and can be used in a wide variety of applications including signal sampling, VSWR measurements, power combining and distribution.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	2		18	GHz
Impedance		50		Ohms
Coupling		30 ±1		dB
Frequency Sensitivity			±1	dB
Insertion Loss		0.9		dB
Directivity	10			dB
Main Line VSWR			1.5:1	
Input Power (CW)			50	Watts

Electrical Specification Notes: Values at 25°C, sea level.

#### **Mechanical Specifications**

Size

 Length
 1.69 in [42.93 mm]

 Width/Dia.
 0.59 in [14.99 mm]

 Height
 0.43 in [10.92 mm]

 Weight
 0.0685 lbs [31.07 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Directional 30 dB SMA Coupler From 2 GHz to 18 GHz Rated to 50 Watts PE2CP000-30

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



# Directional 30 dB SMA Coupler From 2 GHz to 18 GHz Rated to 50 Watts



### Couplers Technical Data Sheet

PE2CP000-30

Configuration

Package TypeConnectorizedInput ConnectorSMA FemaleOutput ConnectorSMA FemaleCoupled ConnectorsSMA Female

**Environmental Specifications** 

**Temperature** 

Operating Range -55 to +85 deg C Storage Range -55 to +100 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

Directional 30 dB SMA Coupler From 2 GHz to 18 GHz Rated to 50 Watts from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Directional 30 dB SMA Coupler From 2 GHz to 18 GHz Rated to 50 Watts PE2CP000-30

URL: https://www.pasternack.com/directional-30-db-sma-coupler-18-ghz-pe2cp000-30-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

# PE2CP000-30 CAD Drawing

Directional 30 dB SMA Coupler From 2 GHz to 18 GHz Rated to 50 Watts

