Data sheet | Item number: 770-754 Snap-in plug; 4-pole; Cod. B; 4,00 mm²; gray www.wago.com/770-754





Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com



Item description

Male connector/plug WINSTA® MIDI with protection type IP20

The *WINSTA*[®] MIDI male connector/plug B coding allows assembly of fine-stranded and solid conductors. WAGO pluggable installation connectors are useful when requirements repeat or are distributed on a specific pattern, for example for installing grid lighting or flush-mount lighting. For greater security in electrical installations, the pluggable installation connector is provided with mechanical protection against mismating. The pluggable installation connector is protected against ingress by solid objects in accordance with protection type IP20 (When mated: IP2xC (These compact connectors are not designed for use in open, easily accessible areas!)). Pluggable installation connectors with B coding from the *WINSTA*[®] MIDI line are available in gray, light green, or pink, allowing you to distinguish different circuits, for example for light, pumps or, sun blinds. Your own pole marking is possible in addition. This pluggable installation connector can be employed for a load of up to 25 A. Therefore, it can also be used for high power loads. The *WINSTA*[®] MIDI Pluggable Connection System with Push-in CAGE CLAMP[®] spring pressure connection technology facilitates precise electrification. Due to the included test slot, connections can be checked even when they are plugged in. This saves time, labor, and money.

Lower costs through fast commissioning and elimination of service expenses – solutions from WINSTA® MIDI

The WINSTA® Pluggable Connection System allows pluggable electrical installation. This significantly reduces the need for servicing and lowers costs. Enjoy the benefits of the pluggable version of our maintenance-free spring pressure connection technology too! Plan your installation with *WINSTA*® MIDI pluggable installation connectors with protection type IP20 from WAGO.

- pluggable installation connectors with protection against mismating
- for automation controllers
- for automation controllers
- exact dimensions
- fast, secure installation

Data

Notes

Variants:	Other pole markings
	Other versions (or variants) can be requested from WAGO Sales or
	configured at https://configurator.wago.com/.

Electrical data

Ratings per IEC/EN

Ratings per

IEC/EN 60664-1

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com



Nominal voltage (III/3)	400 V
Rated impulse voltage (III/3)	6 kV
Rated current	25 A
Note (rated current)	25 A for 3-pole load
	20 A for 4-pole load
Legend (ratings)	(III / 3) ≙ Overvoltage category III / Pollution degree 3

Ratings per UL 1977

Note for the US market	Some versions may also be used for current interruption in accordance with the UL certificate in select applications with currents below 16 A and voltages up to 600 V. For further information, please contact your local sales office.
Rated voltage (UL 1977)	600 V
Rated current UL 1977	23 A

General

Note on contact resistance	approx. 1 m Ω of contact resistance
	approx. 0.25 m Ω contact transition plug/socket
Connection data	

Connection points	8
Total number of potentials	4

Connection 1

Push-in CAGE CLAMP®
Operating tool
Push-in
4 mm² / 12 AWG
0.5 4 mm² / 20 12 AWG
1.5 4 mm² / 16 12 AWG
0.5 2.5 mm² / 20 14 AWG
0.5 4 mm² / 20 12 AWG
0.25 1.5 mm² / 20 16 AWG
0.25 2.5 mm² / 20 14 AWG
1.5 mm² / 16 AWG
9 mm / 0.35 inches
4

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG	Do you have any questions about our products?
Hansastr. 27	We are always happy to take your call at +49 (571) 887-44222.
32423 Minden	
Phone: +49571 887-0 Fax: +49571 887-169	
Email: info.de@wago.com Web: www.wago.com	

Conductor entry direction to mating direction



0 °

Physical data

Pin spacing	10 mm / 0.394 inches
Width	45.5 mm / 1.791 inches
Height	18.5 mm / 0.728 inches
Depth	41.1 mm / 1.618 inches

Mechanical Data

Application	Control technology
Coding	В
Variable coding	Yes
Marking	4321
Potential marking	4321
Mating force of a plug-in connection	approx. 20 70 N (depending on pole number)
Retention force of a plug-in connection	Locked: > 80 N
Unmating force of a plug-in connection	Unlocked: approx. 20 70 N (depending on pole number)
Number of mating cycles	200, without resistive load
Housing sheet thickness	0.5 2 mm / 0.02 0.079 inches
Mounting type	Snap-in flange
Protection type	IP20; When mated: IP2xC (These compact connectors are not designed for use in open, easily accessible areas!)

Plug-in connection

Contact type (pluggable connector)	Male connector/plug
Connector (connection type)	for conductor
Mismating protection	Yes
Note on mismating protection	All <i>WINSTA[®]</i> components are 100% protected against mismating when: a.) plugging different numbers of poles b.) plugging while rotated 180 c.) plugging while laterally staggered d.) plugging one pole
Locking lever	yes
Locking of plug-in connection	locking lever
Note on locking system	All connectors for mounted installations (snap-in versions for lighting fixtures or devices, all types of PCB and distribution connectors) are factory-equipped with locking levers to ensure

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KGDo you have any questions about our products?Hansastr. 27We are always happy to take your call at +49 (571) 887-44222.32423 MindenPhone: +49571 887-0 | Fax: +49571 887-169Email: info.de@wago.com | Web: www.wago.comEmail: info.de@wago.com | Web: www.wago.com



plugs and sockets are securely locked. Additional locking levers are only required for flying leads (plug/socket).

Material Data

Note (material data)

Information on material specifications can be found here

Color	gray
Insulation material	Polyamide (PA66)
Flammability class per UL94	VO
Clamping spring material	Chrome-nickel spring steel (CrNi)
Contact material	Copper or copper alloy; surface-treated
Contact plating	Tin
Fire load	0.457 MJ
Weight	15.9 g

Environmental requirements

Processing temperature	-5 +40 °C
Continuous operating temperature	-35 +85 ℃
Note on continuous operating temperature	Insulating parts for temperatures ≤ 105 °C

Commercial data

20 (Winsta)
27-44-06-02
27-44-06-02
EC002566
EC002566
100 pcs
box
DE
4044918254007
85366990990

Environmental Product Compliance

RoHS Compliance Status

Compliant,No Exemption

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com



Approvals / Certificates

General approvals

Logo	Approval	Additional Approval Text	Certificate name
	CCA DEKRA Certification B.V.	IEC 61984	NL-32104
KEMA	CCA DEKRA Certification B.V.	EN 61984	2173495.01
	cURus Underwriters Laboratories Inc. S	UL 1977	E45171

Declarations of conformity and manufacturer's declarations

Logo	Approval	Additional Approval Text	Certificate name
CE	EU-Declaration of Conformity WAGO GmbH & Co. KG	-	-
UK CA	UK-Declaration of Conformity WAGO GmbH & Co. KG	-	-

Approvals for marine applications

icate
68589-
0001Z6
129487TA

WAGO GmbH & Co. KG	Do you have any questions about our products?
Hansastr. 27	We are always happy to take your call at +49 (571) 887-44222.
32423 Minden	
Phone: +49571 887-0 Fax: +49571 887-169	
Email: info.de@wago.com Web: www.wago.com	



Will Hatt	ltem no.770-244 Socket; 4-pole; Cod. B; 4,00 mm²; gray		www.wago.c	om/770-244
	Item no.771-9994/005-103 pre-assembled interconnecting cable; Eca; Socket/plug; 4-po m; 1,00 mm²; gray	ole; Cod. B; Control cable 4 x 1.0 mm²; 1	www.wago.c /005-103	om/771-9994
	Item no.771-9994/105-103 pre-assembled connecting cable; Eca; Socket/open-ended; 4 1 m; 1,00 mm²; gray	I-pole; Cod. B; Control cable 4 x 1.0 mm²;	www.wago.c /105-103	om/771-9994
Optional ac	cessories			
Operating to	00			
	Item no.: 210-719 Operating tool; Blade: 2.5 x 0.4 mm; with a partially insulated sl	naft	www.wago.	com/210-719
Coding				
Coding				
-	Item no.: 770-401 Coding pin; for plugs; Plastic; gray		www.wago.	com/770-401
Cover				
Cover				
101	Item no.: 770-694 Lockout cap; 4-pole; for cutouts; Plastic; white		www.wago.	com/770-694
101	Item no.: 770-644 Lockout cap; 4-pole; for cutouts; Plastic; black		www.wago.	com/770-644
67997	Item no.: 770-360 Lockout cap; for plugs; 5-pole; separable; yellow		www.wago.com/770-360	
Downloads Documenta				
Bid Text				
770-754		2019 Feb 19	xml	Download
X81 - Datei			3.0 kB	
Subject to cha	anges. Please also observe the further product documentation!			
WAGO GmbH	& Co. KG Do	you have any questions about our produ	ucts?	
Hansastr. 27		e are always happy to take your call at +4		4222

We are always happy to take your call at +49 (571) 887-44222.



770-754	2015 Jun 8	doc 24.6 kB	Download
doc - Datei		24.0 KD	
CAD/CAE-Data			
CAD data			
2D/3D Models 770-754		URL	Download
CAE data			
EPLAN Data Portal 770-754		URL	Download
WSCAD Universe 770-754		URL	Download
ZUKEN Portal 770-754		URL	Download

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 770-754	URL	Download
Snap-in plug; 4-pole; Cod. B; 4,00 mm²; gray		

Installation Notes



We recommend pulling the pre-latched strain relief housing over the cable prior to termination. However, the strain relief can be mounted at a later time as well.

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com







1. Strip length, outer insulation = 35 mm (2pole), 55 mm (3- to 5-pole)

2. Strip length = 9 mm

3. Extended ground conductor = 8 mm

To terminate fine-stranded conductors, open the clamping unit via screwdriver (2.5 mm blade width) and insert a stripped conductor until it hits the backstop.



Insert the stripped solid conductor until it hits the backstop.



To terminate fine-stranded conductors, open the clamping unit via screwdriver (2.5 mm blade width) and insert a stripped conductor until it hits the backstop.

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

Data sheet | Item number: 770-754 www.wago.com/770-754





To remove the conductor, actuate the clamp via screwdriver (2.5 mm blade width) and pull out the conductor.

Product family

WINSTA® MIDI Show all products from the family

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com