

TMMDB3TG

Datasheet

Diac in MINIMELF package with tight V_{BO}



MINIMELF

Features

- V_{BO}: 32 V
- Low breakover voltage: 15 µA max.
- Breakover voltage range: 30 to 34 V

Applications

- General purpose AC line load switching
- Motor control circuits
- Home appliances
- Heating
- Lighting
- Inrush current limiting circuits
- Overvoltage crowbar protection

Description

Functioning as a trigger diode with a fixed voltage reference, the TMMDB3TG can be used in conjunction with Triacs for simplified gate control circuits or as a starting element in fluorescent lamp ballasts.

Product status link		
TMMDB3TG		
Product summary		
Order code	V _{BO}	
TMMDB3TG	30 - 34 V	

1 Characteristics

57

Table 1. Absolute maximum ratings (limiting values), T_j = 25 °C unless otherwise specified

Symbol	Parameter	Value	Unit
I _{TRM}	Repetitive peak on-state current, t_p = 20 µs, F = 120 Hz	2	А
T _{stg}	Storage junction temperature range -40 to +		°C
Tj	Operating junction temperature range	-40 to +125	°C

Table 2. Electrical characteristics (T_j = 25 °C unless otherwise specified)

Symbol	Parameter	Test conditions		Value	Unit
			Min.	30	
V _{BO}	Breakover voltage ⁽¹⁾	C = 10 nF ⁽²⁾	Тур.	32	V
			Max.	34	
I V _{BO1} - V _{BO2} I	Breakover voltage symmetry	C = 10 nF ⁽²⁾	Max.	2	V
ΔV	Dynamic breakover voltage ⁽¹⁾	V_{BO} and V_{F} at 10 mA	Min.	9	V
V _O	Output voltage ⁽¹⁾	See Figure 2. Test circuit , (R = 20 Ω)	Min.	5	V
I _{BO}	Breakover current ⁽¹⁾	C = 10 nF ⁽²⁾	Max.	15	μA
tr	Rise time ⁽¹⁾	See Figure 3. Rise time measurement	Max.	2	μs
۱ _R	Leakage current ⁽¹⁾	$V_R = 0.5 \text{ x } V_{BO} \text{ max}$	Max.	10	μA
lp	Peak current ⁽¹⁾	See Figure 2. Test circuit	Min.	0.30	Α

1. Applicable to both forward and reverse directions.

2. Connected in parallel to the device

Figure 1. Voltage - current characteristic curve.



Figure 2. Test circuit



Figure 3. Rise time measurement



57



1.1 Characteristics (curves)



Figure 6. Triac gate current pulse duration t_p (to have $I_P > 50$ mA) versus Rs and C values (typical values)



Note: according to Figure 2. Test circuit

2 Package information

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK packages, depending on their level of environmental compliance. ECOPACK specifications, grade definitions and product status are available at: www.st.com. ECOPACK is an ST trademark.

2.1 Minimelf package information



Figure 7. MINIMELF package outline

Table 3. MINIMELF package mechanical data

Dim.	mm						
Biili.	Min.	Тур.	Max.	Min.	Тур.	Max.	
A	3.30	3.50	3.70	0.130	0.138	0.146	
В	1.59	1.65	1.70	0.063	0.065	0.067	
С	0.40	0.50	0.60	0.016	0.020	0.024	
D		1.50			0.059		





Figure 8. MINIMELF recommended footprint (dimensions are in mm)

3 Ordering information

57

Figure 9. Ordering information scheme



Table 4. Ordering information

Orc	der code	Marking	Package	Weight	Base qty.	Delivery mode
TMI	MDB3TG	(None)	Minimelf	0.04 g	2500	Tape and reel

Revision history

Table 5.	Document	revision	history
----------	----------	----------	---------

Date	Version	Changes
January-2001	2	Previous release.
07-May-2019	3	Updated Section 1.1 Characteristics (curves) and Table 3. MINIMELF package mechanical data. Minor text change to improve readability.



IMPORTANT NOTICE - PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, please refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2019 STMicroelectronics – All rights reserved