### **Model PSxx**

#### Features:

- 100,000 cycle life
- Metal/plastic lever
- RoHS Compliant





## **Model Styles Available**

Single Gang	PSxx-1
Dual Gang	PSxx-2

## **Electrical**<sup>1</sup>

Resistance Range, Ohms	1K - 1M				
Standard Resistance Tolerance	± 20%				
Resistance Tapers	A, B, C				
Residual Resistance	Terminals 1 to 2: less than 10 ohms Terminals 2 to 3: less than 30 ohms				
Input Voltage, Maximum	Linear B taper: 200 Vac Other tapers: 150 Vac				
Power Rating, Watts (Single Unit / Dual Unit)	Linear B taper: 20mm: 0.1W / 0.05W, 30mm : 0.2W / 0.1V 45mm: 0.25W / 0.125W, 60mm : 0.2W / 0.2V				
	<b>Other tapers:</b> 20mm: 0.05W / 0.025W, 30mm : 0.1W /0.05W 45mm: 0.125W / 0.06W, 60mm : 0.1W / 0.1W				
Dielectric Strength	300 Vac, 1 minute				
Insulation Resistance, Minimum	100M ohms at 250Vdc / 1 minute				
Sliding Noise	Less than 100mV				
Gang Error	±3dB (-40dB to 0dB)				

#### Notes:

<sup>1</sup> Specifications subject to change without notice

General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

## Model PSxx



### Mechanical

Static Stop Strength, Minimum	5.0 Kgf/cm
Operating Force	10gf to 100gf
Detent Slip-out force	30gf to 200gf

### Durability



**Ordering Information<sup>2</sup>** PS30 - 1 0 P C 1 B R100K D \_\_\_\_ \_\_\_\_\_ Dust Cover: Blank= No dust cover Model Style D = Plastic dust cover R = Black felt dust cover Tapers: Travel in millimeters **Total Resistance** A = Audio 15, 20, 30, 45, 60 B = Linear C = Reverse Audio Number of Gangs: Lever Material: Detent Lever Length: 1 = Sinale P = Plastic See "L" Code 2 = Dual0 = WithoutM = Metal Lever Type: 1 = Center **Below** See Below

### **Standard Resistance Values, Ohms**

1K 2K 5K 10K 20K 50K 100K 200K 500K 1 ME
--

#### Notes:

<sup>2</sup> Contact our customer service for custom designs and features

General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

## Model PSxx



### **Plastic Lever Types**



### **Metal Lever Types**



General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

**Model PSxx** 



## **Outline drawing**

### **PSxx-1 Single Gang**



#### **PSxx-2 Dual Gang**



General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

Model PSxx



MODEL	А	В	С	D	E	F	G
PS15-1	30	26	15	17.8	20.2	28.8	
PS15-2	30	26	15	17.8	20.2	28.8	18
PS20-1	35	31	20	22.8	25.2	33.8	
PS20-2	35	31	20	22.8	25.2	33.8	23
PS30-1	45	41	30	32.8	35.2	43.8	
PS30-2	45	41	30	32.8	35.2	43.8	33
PS45-1	60	56	45	47.8	50.2	58.8	
PS45-2	60	56	45	47.8	50.2	58.8	48
PS60-1	75	71	60	62.8	65.2	73.8	
PS60-2	75	71	60	62.8	65.2	73.8	63

### **Circuit Diagram**

#### **PSxx-1 Single Gang**



#### PSxx-2 Dual Gang



General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.