

3,5

26

www.wago.com/770-895/080-000



Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com



Item description

Male connector/plug WINSTA® MIDI B coding

The *WINSTA®* MIDI male connectors/plugs rated current 25 A are compact but powerful PCB terminal blocks. They offer easy operation and the greatest flexibility for installation. Our extensive selection of pluggable PCB connectors with various insertion directions and operating variants offers you the right solution for your application at all times.

The coding options reduce installation errors, allowing fast, secure wiring of all components. The harmonised interface for motor control allows easy installation and activation of sun protection and shading systems. Solutions like the *WINSTA*[®] MIDI pcb connectors with B coding are suitable for process control, such as for lighting or within data networks. The rated current and voltage are important criteria for selecting a pcb connector: They tell us about the product's domains of use. This product has a current rating of 25 A – therefore it is also suitable for high power loads. *WINSTA*[®] MIDI with Push-in CAGE CLAMP[®] spring pressure connection technology is used in a broad range of individual products you can use for quick, easy and maximally flexible electrical installation.

WINSTA® MIDI solutions for your electrical installation – protected against mismating and maintenance-free

WINSTA® is the pluggable connection system that is ideally tailored to the strict requirements of electrical installation. It offers fast, secure and, above all, error-free installation of components and cables. Choose durability and quality – the *WINSTA®* MIDI pcb connector with locking lever from WAGO makes the installation of electrical components noticeably easier.

- protection against mismating eliminates errors
- for automation controllers
- for automation controllers

Email: info.de@wago.com | Web: www.wago.com

fast, secure installation

Data

Notes

Variants:	Other pole markings Other versions (or variants) can be requested from WAGO Sales or configured at https://configurator.wago.com/
Electrical data	
Note on contact resistance	approx. 1 m Ω of contact resistance
	approx. 0.25 m Ω contact transition plug/socket
Ratings per	IEC/EN 60664-1
Subject to changes. Please also observe the further produ	uct documentation!
WAGO Kontakttechnik GmbH & Co. KG	Do you have any questions about our products?
Hansastr. 27	We are always happy to take your call at +49 (571) 887-44222.
32423 Minden	
Phone: +49571 887-0 Fax: +49571 887-169	

13.10.2021 Page 2/7



Nominal voltage (III/3)	400 V
Rated surge voltage (III/3)	6 kV
Rated current	25 A
Legend (ratings)	(III / 3) ≙ Overvoltage category III / Pollution degree 3
Hinweis für den amerikanischen Markt	Application note for the U.S. market (USR): Some versions may also be used for current interruption in accordance with the UL certificate in select applications with currents below 16 A and voltages up to 600 V. For further information, please contact your local sales office.
Rated voltage UL 1977	600 V
Rated current UL 1977	23 A

Connection data

Total number of potentials	5
Number of levels	1
Pole No.	5

Physical data

Pin spacing	10 mm / 0.394 inch
Width	47 mm / 1.85 inch
Height	29.5 mm / 1.161 inch
Height from the surface	26 mm / 1.024 inch
Depth	14.6 mm / 0.575 inch
Solder pin length	3.5 mm
Solder pin dimensions	1 x 0.8 mm
Drilled hole diameter with tolerance	1.5 ^(-0.1 +0.1) mm

Mechanical data

technology	SMI
Application	Measurement and regulation technology
Coding	В
Marking	N ≑ L I- I+
Potentialkennzeichnung	N ≟ L I- I+
Mating force of a plug-in connection	approx. 20 70 N (depending on pole number)
Retention force of a plug-in connection	Locked: > 80 N
Unmating force of a plug-in connection	Unlocked: approx. 20 70 N (depending on pole number)
Number of mating cycles	200, without resistive load

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

www.wago.com/770-895/080-000



straight

Plug-in connection

Design

Contact type (pluggable connector)	Male connector/plug
Connector (connection type)	for PCB
Mismating protection	Yes
Note on mismating protection	All WINSTA [®] components are 100% protected against mismating when: a.) plugging different numbers of poles b.) plugging while rotated 180 c.) plugging while laterally staggered d.) plugging one pole
Mating direction to the PCB	90°
Locking lever	yes
Locking of plug-in connection	locking lever
Hinweis zur Verriegelung	All connectors for mounted installations (snap-in versions for lighting fixtures or devices, all types of PCB and distribution connectors) are factory-equipped with locking levers to ensure plugs and sockets are securely locked. Additional locking levers are only required for flying leads (plug/socket).

PCB contact

PCB Contact	ТНТ
Solder pin arrangement	2 in-line solder pins/pole
Number of solder pins per potential	2

Material data

Color	pink
Insulation material	Polyamide (PA66)
Clamping spring material	Chrome nickel spring steel (CrNi)
Contact material	Copper or copper alloy (surface-treated)
Fire load	0.231 MJ
Weight	10.8g

Environmental requirements

Processing temperature	-5 +40 °C
Continuous operating temperature	-35 +85 ℃
Note on continuous operating temperature	Insulating parts for temperatures ≤ 105 °C

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KGDo you have any questions about our products?Hansastr. 27We are always happy to take your call at +49 (571) 887-44222.32423 MindenPhone: +49571 887-0 | Fax: +49571 887-169Email: info.de@wago.com | Web: www.wago.comEmail: info.de@wago.com | Web: www.wago.com



Commercial data

PU (SPU)	50 Stück
Packaging type	box
Country of origin	PL
GTIN	4050821553939
Customs tariff number	85366990990

Other

tecl	nno	logy	
1001	1110	iugy	

SMI

Approvals / Certificates

UL-Approvals

			Certificate
Logo	Approval	Additional Approval Text	name
	cURus	UL 1977	E45171
c SL us	Underwriters Laboratories Inc.		

Counterpart

Item no.770-285/080-000 Socket; 5-pole; Cod. B; 4,00 mm²; pink	www.wago.com/770-285/080-000
Item no.771-9935/006-107/080-000 pre-assembled interconnecting cable; Eca; Socket/plug; 5-pole; Cod. B; H05VV-F 5G 1.5 mm ² ; 1 m; 1,50 mm ² ; pink	www.wago.com/771-9935/006-107 /080-000
Item no.771-9935/106-107/080-000 pre-assembled connecting cable; Eca; Socket/open-ended; 5-pole; Cod. B; H05VV-F 5G 1.5 mm ² ; 1 m; 1,50 mm ² ; pink	www.wago.com/771-9935/106-107 /080-000

Required accessories

Cover

Cover

Item no.: 770-360 Lockout cap; for plugs; 5-pole; separable; yellow

www.wago.com/770-360

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

Optional accessories

Coding



Coding



Item no.: 770-401 Coding pin; for plugs; Plastic; gray

Downloads CAD/CAE-Data

2D/3D Models 770-895/080-000	URL	Download

PCB Design Symbol and Footprint 770-895/080-000 URL Download CAx data for your PCB design, consisting of "schematic symbols and PCB footprints", allow easy integration of the WAGO component into your development environment. Supported formats: Accel EDA 14 & 15 Altium 6 to current version Cadence Allegro DesignSpark **Eagle Libraries** KiCad Mentor Graphics BoardStation Mentor Graphics Design Architect Mentor Graphics Design Expedition 99 and 2000 OrCAD 9.X PCB and Capture PADS PowerPCB 3, 3.5, 4.X, and 5.X PADS PowerPCB and PowerLogic 3.0 PCAD 2000, 2001, 2002, 2004, and 2006 Pulsonix 8.5 or newer STL **3D STEP TARGET 3001!** View Logic ViewDraw Quadcept

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.



www.wago.com/770-401



- Zuken CadStar 3 and 4
- Zuken CR-5000 and CR-8000

PCB Component Libraries (EDA), PCB CAD Library Ultra Librarian

CAE data URL Download ZUKEN Portal 770-895/080-000 URL Download Environmental Product Compliance V V Compliance Search URL Download Environmental Product Compliance 770-895/080-000 URL Download Plug for PCBs; straight; 5-pole; Cod. B; pink URL Download

Installation Notes

Product family

WINSTA® MIDI Show all products from the family

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com