



PLL Part No: PT1300-1005-GPS

Issue 2; 29th April 2022

Features

- Temperature stability locked to ± 0.001 ppb long term
- Low phase noise
- Frequency range 10MHz
- Low pre-aged options available
- Small surface mount package
- The flexible nature of the design means that variations to suit almost any application can be developed to meet individual customer requirements



Specifications

- Temperature stability unlocked: ±20ppb over (-40 to 70)^oC
- Output: Sinewave 7dBm
- Voltage: 5.0V
- Warm Up Current: 540mA
- Quiescent current: 270mA

Phase Noise (typical)

- F0₀+10Hz -120 dBc/Hz
- F0₀+100Hz -140 dBc/Hz
- F0₀+1KHz -155 dBc/Hz
- F0₀+10KHz -165 dBc/Hz
- F0₀+100KHz -168 dBc/Hz

Voltage/ Load change

- ±5% supply voltage change: ±2ppb
- ±10% load change: ±5ppb

Ageing:

Based on 10MHz unit after 30 days continuous operation:

- Per day: ±0.1ppb max.
- Per year: ±50ppb max.
- Warm up time: 5 minutes to within 1 ppm

1pps accuracy:

±50 ns

Antenna reference (If used)

• 3V

Environmental

- Electrostatic-Sensitive Device (ESD)
- Storage Temperature Range: (-40 to 1+25)°C
- Mechanical shock: MIL standard 202F, method 213, condition J
- Thermal shock: MIL standard 202F, method 107, condition A





<pre>#1 ground #2 antenna #3 ground #4 antenna bias #5 d.c bias out #6 ground #7 NMEA (CMOS RS232) #8 ground #9 RF out</pre>		#13 N/C #12 lock 2
#10 ground		#11 lock 1
Lock Status		
Lock 1 low high/low high low high	Lock 2 low low/high low high high	no status power up test OK GPS satellite detect GPS Lock Full operational lock





- Solderability: 5 seconds maximum at 230°C
- 3 seconds maximum at 350°C

Compliance

- RoHS Status (2011/65/EU) Compliant
- REACH Status Compliant

Packaging

Pack Style: Bulk

Ordering Information

- Unique customer part number and custom specification issued with each application
- PLL Part No.: PT1300-1005-GPS



Test Circuit - Sinewave

