

8 dB Fixed Attenuator, 2.92mm Male to 2.92mm Female Passivated Stainless Steel Body Rated to 2 Watts Up to 40 GHz



# **RF Fixed Attenuators Technical Data Sheet**

## PE7430-8

## Tixed Attendators reconnect i

VSWR < 1.35:1</li>

Max Power 2 Watts (CW)

Bidirectional

**Features** 

- DC to 40 GHz Frequency Range
- Attenuation 8dB Typical

#### **Applications**

- Instrumentation
- Precision measurements
- Prototyping and characterization
- Production systems

#### Description

Pasternack carries a wide range of fixed attenuators with a broad selection of attenuation levels, frequency ranges, and power dissipation ranges. RF microwave attenuators (also known as RF pads) lower the amplitude of a signal (attenuate) a known amount and can be used in a wide variety of applications. These attenuator pads are used when a signal needs to be reduced to protect measurement equipment or other circuitry, to extend the range of power meters and amplifiers, and to impedance match circuits by reducing the VSWR seen by adjacent components. RF attenuators can prevent signal overload in amplifiers, receivers and detectors, adjusting the signal level to a range that is optimal.

Few RF components are as commonly used as fixed coaxial attenuators, and Pasternack carries one of the largest in-stock varieties and ships them same day. The 8 dB Fixed Attenuator PE7430-8 is rated to 2 Watts and operates from DC to 40 GHz. The versatile coaxial package uses 2.92mm male to 2.92mm female connectors and is also REACH and RoHS compliant.

### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		40	GHz
Impedance		50		Ohms
Nominal Attenuation		8		dB
Attenuation Accuracy			1	dB
VSWR			1.35:1	
Input Power, CW			2	Watts
Input Power, Peak	-		200	Watts
5 µs pulse, 1% Duty Cycle				

#### **Mechanical Specifications**

Size Weight Body Material and Plating

0.45 lbs [204.12 g] Passivated Stainless Steel

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 8 dB Fixed Attenuator, 2.92mm Male to 2.92mm Female Passivated Stainless Steel Body Rated to 2 Watts Up to 40 GHz PE7430-8

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com



800-8 800-8

PE7430-8

# **RF Fixed Attenuators Technical Data Sheet**

8 dB Fixed Attenuator. 2.92mm Male to 2.92mm Female

Passivated Stainless Steel Body Rated to 2 Watts Up to 40 GHz

Configuration Fixed Design Connectors Description **Connector 1 Connector 2** 2.92mm Male 2.92mm Female Type Beryllium Copper, Gold Beryllium Copper, Gold Contact Material and Plating Coupling Nut Material and Plating Stainless Steel Body Material and Plating Passivated Stainless Steel Passivated Stainless Steel

#### **Environmental Specifications**

Temperature Operating Range

-55 to 125 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

8 dB Fixed Attenuator, 2.92mm Male to 2.92mm Female Passivated Stainless Steel Body Rated to 2 Watts Up to 40 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 8 dB Fixed Attenuator, 2.92mm Male to 2.92mm Female Passivated Stainless Steel Body Rated to 2 Watts Up to 40 GHz PE7430-8

URL: https://www.pasternack.com/8db-fixed-2.92mm-male-2.92mm-female-2-watts-attenuator-pe7430-8-p.aspx

# PE7430-8 CAD Drawing

8 dB Fixed Attenuator, 2.92mm Male to 2.92mm Female Passivated Stainless Steel Body Rated to 2 Watts Up to 40 GHz

